



TimeSync function brings time-synchronization over the Wireless IOT Sensors Network (±2.5ms of accuracy between each wireless IOT sensor) and contributes to enhance user experience about correlation of remote sensing data and modal analysis.



#### **REMOTE CONFIGURATION & MONITORING**

#### BeanScape<sup>®</sup> 2.4GHz Basic

BeanAir Wireless lot sensors

A powerful and versatile supervision software for managing your wireless sensors

The\_BeanScape<sup>®</sup> 2.4GHz allows the user to view and manage all the data transmitted by the BeanDevice<sup>®</sup> 2.4GHz HI-INC -SR Thanks to the OTAC (Over-the-Air configuration) function, users can remotely configure the BeanDevice<sup>®</sup> 2.4GHz HI-INC-SR. A versatile wireless inclinometer with different data acquisitions mode:

- Low Duty Cycle Data Acquisition mode (LDCDA): Data acquisition is immediately transmitted by radio. Transmission frequency can be configured from the BeanScape<sup>®</sup> 2.4GHz software from 1s to 24h.
- Survey Mode: An alarm notification is transmitted when a threshold is reached. A powerful alarm management tool available on the BeanScape<sup>®</sup> 2.4GHz software allows the user to configure alarm threshold and to generate automatic alarm notification by email. A "heart beat" notification is frequently transmitted, and keeps the user informed about its current status.
- Streaming Mode : All measured data are transmitted by packet within a continuous flow at 60 samples per second maximum



For further information about the different data acquisition modes: TN-RF-008 – "Data acquisition modes available on the BeanDevice®"

#### ANTENNA DIVERSITY

While the vast majority of wireless IOT sensors show their limits in harsh industrial environment, the BeanDevice<sup>®</sup> 2.4GHz HI-INC-SR integrates an innovative antenna diversity design, boosting the radio link quality in environments subject to random and diverse disturbances. Antenna Diversity improves both the quality and reliability of a wireless link by 30%



#### EMBEDDED DATA LOGGER UP TO 8 MILLION DATA POINTS

The BeanDevice<sup>®</sup> 2.4GHz HI-INC-SR integrates an embedded datalogger, which can be used to log data when a Wireless IOT Sensors can not be easily deployed on your site. All the data acquisition are stored on the embedded flash and then transmitted to the BeanGateway<sup>®</sup> 2.4GHz when a Wireless IOT Sensors is established.

The data logger function is compatible with all the data acquisition mode available on the BeanDevice<sup>®</sup> 2.4GHz HI-INC-SR :

- LowDutyCycle Data Acquisition
- Survey
- Streaming packet

BeanAir Wireless lot sensors

#### EXAMPLE : TILT MONITORING ON A BRIDGE

• In standalone operation, the BeanDevice<sup>®</sup> 2.4GHz HI-INC-SR stores all the measurements on its onboard datalogger. Thus, a direct connection with the BeanGateway<sup>®</sup> 2.4GHz\_is not needed.

- During the measurement campaign, all the acquired measurements are stored on datalogger.
- Data logs can be transmitted to the BeanGateway<sup>®</sup> 2.4GHz on request. Once a successful transmission is done, the user can choose to erase automatically the logs from the datalogger memory, so new ones can be stored.



For further information about data logger, please read the following technical note : TN-RF-007 – "BeanDevice® DataLogger User Guide "

#### TECHNICAL SPECIFICATIONS

BeanAir WIRELESS IOT SENSORS

#### **PRODUCT REFERENCE**

#### BND-2.4Hz-HI-INC-SR -MR-PS-MO-HG

MR – Measurement Range: PS - Power Supply 10T : Tri-axial ±10°/±90° RB : Internal recha battery XT : External power (Compatible with )

RB : Internal rechargeable battery XT : External power supply 4VDC ( Compatible with X-SOLAR-4VDC and PRIM-XTENDER) MO - Mounting Option SCM - Screw Mounting base MM - Magnetic Mounting base

#### HG: High Gain External Antenna 5dBi If this field is left blank,

Integrated Radome Antenna will be provided

Example 1: BND-2.4GHZ-HI-INC-SR-10T-SCM, High performance wireless Tri-axis inclinometer with ±10°/±90° measurement range, internal rechargeable battery, Screw mounting, Integrated Radome Antenna Example 2: BND-2.4GHZ-HI-INC-SR-10T-XT-MM, High performance wireless Tri-axis inclinometer with ±10°/±90° measurement range, external power supply, Magnetic Mounting, Integrated Radome Antenna Example 3: BND-2.4GHZ-HI-INC-SR-10T-SCM-HG, High performance wireless Tri-axis inclinometer with ±10°/±90° measurement range, internal rechargeable battery, Screw mounting, External High Gain Antenna

#### **SENSOR SPECIFICATIONS**

Inclinometer Technology	Accurate and low power MEMS technology	
Scalable Measuring Range	uer-seletctable range ±10° or ±90°, with automatic range adjustment depending on the application	
Sensor resolution	0.0055°	
Noise density	for ±10° range : 0.0007 °/√Hz on Y Axis, 0.008 °/√Hz on X, Z Axis for ±90° range : 0.0012 °/√Hz on all axis	
Sensor precision (full scale, @ 25°C, Static Measurement Mode every 2s)	±0.01° for ±10° measurement range ±0.02° for ±90° measurement range	
Offset temperature dependency (temperature range $-25$ °C to +85 °C)	±0.0008 °/°C	
Sensitivity temperature dependency (temperature range -25°C to +85°C)	±0.1 %	
Offset LifeTime Drift (@25°C)	±0.08°	
Sensor frequency Response (-3 dB)	DC to 10 Hz for ±10° measurement range DC to 40 Hz for ±90° measurement range (Automatic Range) DC to 70 Hz for ±90° measurement range	
Calibration	Factory calibrated for ±10° range and ±90° with calibration settings backed up on the sensor Flash memory. Calibration method used : Back-to-back calibrated with a reference sensor. Re-calibration procedures are available on our website, and sensor can be re-calibrated by the user or with an external Lab	
INTEGRATED TEMPERATURE SENSOR		
Temperature Range	-40°C to +75°C	
Measurement resolution	±0.06°C	
Sensor Precision	±1°(	





#### **TECHNICAL SPECIFICATIONS**

CONFIGURABLE SETTINGS FROM THE BEANSCAPE® 2.4GHZ SOFTWARE	
Data Acquisition mode (SPS = sample per second)	Static Data Acquisition: Low Duty Cycle Data Acquisition (LDCDA) and Alarm Mode (based on alarm thresholds). Measurement heartbeat 1s to 24 hour Dynamic data acquisition(not available on devices with ref. extension XT ): Streaming and S.E.T. (Streaming with Event Trigger) Mode
Sampling Rate (in streaming and S.E.T. mode)	Minimum: 1 SPS Maximum: 20 SPS on each axis, for ±10° measurement range (Static and Auto Range), for ±90° measurement range Auto Range), Maximum: 80 SPS on each axis, for ±90° measurement range (Static Range)
Alarm Threshold	Three-level alarms : Alert < Action < Alarm
Scalable Mesurement Range	±10° , ±90° and automatic ±10°/±90°
Power Mode	Battery saver mode & Active power mode (Active Power Mode is not available on -XT version)
RF SPECIFICATIONS	
Wireless Technology	Ultra-Low-Power and license-free 2.4Ghz radio technology (IEEE 802.15.4E)
WSN Topology	Point-to-Point / Star
Data rate	250 Kbits/s
RF Characteristics	ISM 2.4GHz – 16 Channels. Antenna diversity

	designed by Beanair®
TX Power	+18 dBm
Receiver Sensitivity	-104dBm
Maximum Radio Range (In Transmission Mode)	High Gain Antenna : 400-500m (L.O.S), 60-120m (N.L.O.S.) Integrated Radome Antenna : 200-300m (L.O.S), 30-60m (N.L.O.S.)

Antenna

High Gain Antenna : 2 x N-Type Antenna 5dBi , IP67 Radome Antenna : 2 x Antenna 1.9 dBi , IP67

#### EMBEDDED DATA LOGGER

Storage capacity Wireless data downloading up to 8 millions data points 20 minutes to download the full memory (average time)

#### TIMESYNC FUNCTION : CLOCK SYNCHRONIZATION OVER THE WIRELESS IOT SENSORS

Clock synchronization accuracy Crystal specifications ±2.5 ms (at 25°C)

Antenna diversity :

Tolerance ±10ppm, stability ±10ppm



BeanAir WIRELESS IOT SENSORS

#### **ENVIRONMENTAL AND MECHANICAL**

Casing	<ul> <li>Aluminum AL6061 &amp; Waterpoof casing</li> <li>Dimensions in mm (LxWxH): 100 x 71 x 38 (without Radome antennas, with mounting eyelet)</li> <li>Weight (with internal battery &amp; Radome Antenna) : 240g (screw mounting)</li> <li>265g (magnetic mounting)</li> <li>Weight (with internal battery &amp; High Gain Antenna) : 440g (screw mounting)</li> <li>465g (magnetic mounting)</li> </ul>
IP   NEMA Rating	IP67   Nema 6
Shock resistance	150g during 50 ms
Operating Temperature	RB : Internal rechargeable battery -40 °C to +60 °C XT : External Power Supply -40 °C to +75 °C during battery discharge A Sunshield must be used if the sensor is exposed to direct sun radiation.
Norms & Radio Certifications	<ul> <li>CE Labelling Directive R&amp;TTE (Radio) ETSI EN 300 328</li> <li>FCC (North America)</li> <li>ARIB STD-T66 Ver 3.6</li> <li>ROHS - Directive 2002/95/EC</li> </ul>
Maximum Humidity	90 %RH
Base Plate	<ul> <li>-Aluminum black anodized AL 7075 with rugged three-point-mounting</li> <li>-Screw Mounting Option: the device should be mounted on a flat and smooth surface with 3 screws, dimension M5. Mounting torque 5 ±1Nm</li> <li>-Magnetic Mounting Option: the device should be mounted on a steel surface.</li> </ul>

POWER SUPPLY		
Integrated battery charger	<ul> <li>Integrated Lithium-ion battery charger with high precision attery monitoring :</li> <li>Overvoltage/Overcurrent/Short-Circuit/ Undervoltage protection</li> <li>Battery Temperature monitoring</li> </ul>	
Current consumption @3.3V	<ul> <li>During data acquisition : 30 to 40 mA</li> <li>During Radio transmission : 55 mA @ 18 dBm</li> <li>During Battery Saver Mode : &lt; 30 μA</li> </ul>	
External power supply	8-28VDC with reverse polarity protection IEC-61000-4-2: ESD 30kV(Air), 30kV (Contact) Surge protection > 28VDC (600W during 10us max)	
Rechargeable battery	2 Ah, Lithium-Polymer battery	

**2.4**: GH





#### **INCLUDED ACCESSORIES**

1x Magnet to Power ON/Power OFF the device 1x M8 Cap for Power Supply

#### **OPTIONAL ACCESSORIES AND SERVICES**

External Power Supply	Wall plug-in, Switchmode power Supply 12V @ 1,25A with sealed M8 Plug (IP67/Nema 6) Ref : M8-PWR-12V
Solar Panel Kit (compatible with External Power Supply version only)	High efficiency solar panel with Solar charging controller and Lead-acid battery Ref.: X-SOL-7AH-20W-4V-5M for XT version Ref: X-SOL-7AH-20W-12V-5M for RB version Ref: X-SOL-14AH-20W-4CH-4V-5M for XT version Ref: X-SOL-14AH-20W-4CH-12V-5M for XT version Ref: X-SOL-14AH-80W-4CH-4V-5M for XT version Ref: X-SOL-14AH-80W-4CH-12V-5M for RB version
Bracket Mounting	90° Bracket for BeanDevice (Xrange smartsensor) with 4 x M5 screws + Locknut Ref : SMART-BRACK-MNT
External Primary Cell in a Waterproof IP67 Casing	Waterproof IP67 battery box for long-term monitoring applications IP67 Battery Holder + Battery Pack with 3 x 6500mAh Li-SOCL2 Lithium Primary cell (Capacity 3x 6.5Ah) Ref : PRIM-XTENDER Compatible with : BND-2.4GHZ-HI-INC-SR-10T-XT-MM & BND-2.4GHZ-HI-INC-SR-10T-XT-SCM
M8 extension cable for external power supply	Molded cable with M8-3pins male plug Material: PVC with shield protection IP Rating : IP67   Nema 6 Cable length : 2 meters, Ref : CBL-M8-2M Cable length : 5 meters, Ref : CBL-M8-5M Cable length : 10 meters, Ref : CBL-M8-10M
Calibration certificate	Calibration certificate provided by Beanair GmbH A static calibration method is used on a granite surface plate DIN876 Ref : CERT-CAL-SMART

500m L.O.S conditions is reached: • Beangateway is positioned in Line Of Sight toward sensor (no obstacles, no radio interferences) with High Gain Antenna, with a Height of 3 meters minimum. 26dBm High Gain Directional Antenna is used om gateway side. • On sensor side : Radome Antenna should point to Vertical Direction for better Coverity



Product specifications are subject to change without notice. Contact Beanair for latest specifications.

#### **EXTERNAL POWER SUPPLY WIRING CODE**







Do not power PIN4 and PIN3 at the same time, you will damage your Beandevice

#### OPTIONS AND ACCESSORIES



### M8 extension cable for external power supply

Molded cable with M8-3pins male plug Material: PVC with shield protection IP Rating : IP67 | Nema 6 Cable length: 2 meters , Ref: CBL-M8-2M Cable length : 5 meters, Ref: CBL-M8-5M Cable length: 10 meters, Ref: CBL-M8-10M

Solar charging controller and Lead-acid battery Ref.: X-SOL-7AH-20W-1CH-4V-5M for XT version Ref.: X-SOL-7AH-20W-1CH-12V-5M for RB version Ref: X-SOL-14AH-20W-4CH-4V-5M for XT version Ref: X-SOL-14AH-20W-4CH-12V-5M for RB version Ref: X-SOL-14AH-80W-4CH-4V-5M for XT version Ref: X-SOL-14AH-80W-4CH-12V-5M for RB version



#### **External Power-Supply**

Wall plug-in, Switchmode power Supply 12V @ 1,25A with sealed M8 Plug ( IP67/Nema 6) Ref: M8-PWR-12V

#### Solar Panel Kit





#### Mechanical Mounting Options

- 90° Bracket for BeanDevice (Xrange smartsensor) with 4 x M5 screws + Locknut Ref: SMART-BRACK-MNT
- Magnetic Mounting Lid

10

BeanAir WIRELESS IOT SENSORS

# BeanDevice<sup>®</sup> 2.4GHZ HI-INC-SR



2.

С